

Control4® Wireless Keypad Dimmer



- Control4® Wireless Keypad Dimmer, 120V—C4-KD120
- Control4® Wireless Keypad Dimmer, 240V—C4-KD240
- Control4® Wireless Keypad Dimmer, 277V—C4-KD277

The Control4® Wireless Keypad Dimmer combines the dimming capabilities of the Control4® Wireless Adaptive Phase Dimmer with the flexibility of the Control4® Wireless Configurable Keypad. Unlock the power of one-touch automation simply by replacing an existing light switch with a Keypad Dimmer.

- Turns a standard light switch or dimmer into a fully customizable keypad and dimmer
- Includes a button kit with every button necessary to make any of the 37 possible button configurations
- Compatible with a variety of load types including LEDs, Incandescent, Halogen, Electronic Low Voltage (solid state) Transformers, Magnetic (iron core) Low Voltage Transformers, Fluorescents, Compact Fluorescents
- Supports both forward phase (leading edge) and reverse phase (trailing edge) dimming
- Automatically detects load type and determines the appropriate dimming type
- Protection circuitry prevents device damage in case of short circuit or excessive load
- Continuously measures energy being used by the attached load
- Elegant, sophisticated design makes a beautiful addition to any home or business
- Custom engraving available to clearly identify each button
- Backlit button engraving with programmable color control for easy readability regardless of time of day or light level
- Programmable RGB LEDs provide status feedback for lighting and other devices in the system
- Ambient light sensor automatically adjusts backlight and status LED brightness depending on the light level in the room
- Available in a wide array of gloss and satin colors (See Available Colors)
- Control4® screw-less faceplates, sold separately, provide a sleek profile (See Available Accessories)

Control4® Wireless Keypad Dimmer

| | | | |
|--|--|---------------|----------------|
| Model Numbers | C4-KD120, C4-KD240, C4-KD277 | | |
| Power Requirements | C4-KD120: 120VAC +/-10%, 50/60Hz C4-KD240: 220VAC +/-10%, 50/60Hz C4-KD277: 277VAC +/-10%, 50/60Hz This device can function with or without a neutral AC connection depending on load type. | | |
| Power Consumption | C4-KD120: 450mW C4-KD240: 2.02W C4-KD277: 550mW | | |
| Load Types and Ratings | | | |
| Supported Load Types | Incandescent; Halogen; Electronic (Solid State) Low Voltage (ELV) Transformers, Magnetic (Iron Core, Inductive) Low Voltage (MLV) Transformers; Phase-Dimmable Fluorescents, Compact Fluorescents, and LEDs. | | |
| C4-KD120 Maximum Load | | | |
| | 1 Gang | 2 Gang | 3+ Gang |
| Incandescent (Tungsten) | 600W | 550W | 500W |
| Halogen | 600W | 550W | 500W |
| Fluorescent* | 300W | 300W | 300W |
| Compact Fluorescent (CFL)* | 300W | 300W | 300W |
| LED* | 120W | 120W | 120W |
| C4-KD240 Reverse Phase Maximum Load | | | |
| | 1 Gang | 2 Gang | 3+ Gang |
| Incandescent (Tungsten) | 800W | 700W | 600W |
| Halogen | 800W | 700W | 600W |
| Fluorescent* | 500W | 500W | 500W |
| Compact Fluorescent (CFL)* | 500W | 500W | 500W |
| LED* | 160W | 160W | 160W |
| C4-KD240 Forward Phase Maximum Load | | | |
| | 1 Gang | 2 Gang | 3+ Gang |
| Incandescent (Tungsten) | 400W | 400W | 400W |
| Halogen | 400W | 400W | 400W |
| Fluorescent* | 400W | 400W | 400W |
| Compact Fluorescent (CFL)* | 400W | 400W | 400W |
| LED* | 160W | 160W | 160W |
| C4-KD277 Maximum Load | | | |
| | 1 Gang | 2 Gang | 3+ Gang |
| Incandescent (Tungsten) | 1000 | 900 | 800 |
| Halogen | 1000 | 900 | 800 |
| Fluorescent* | 500 | 500 | 500 |
| Compact Fluorescent (CFL)* | 500 | 500 | 500 |
| LED* | 200 | 200 | 200 |
| Minimum Load (with neutral), All Models | | | |
| All load types | 1W | | |
| Minimum Load (without neutral) | | | |
| Incandescent (Tungsten) | 7W | | |
| Halogen | 7W | | |
| Fluorescent* | N/A | | |
| Compact Fluorescent (CFL)* | N/A | | |
| LED* | N/A | | |

*NOTES: 1) The maximum load requirements for fluorescent, CFL and LED loads can vary greatly depending upon the specific fixture and/or bulb being used. 2) The quality and performance of these load types varies greatly from manufacturer to manufacturer. 3) The use of fluorescent, CFL, or LEDs load without a neutral wire connected to the dimmer is not recommended.



Control4® Wireless Keypad Dimmer

| Environmental | |
|--|---|
| Operational Temperature | 32° F - 104° F (0° C - 40° C) All load ratings are based on an ambient temperature of 25° C. |
| Humidity | 5% to 95% non-condensing |
| Storage | -4° F - 158° F (-20° C - 70° C) |
| Miscellaneous | |
| Control Communications | ZigBee, IEEE 802.15.4, 2.4 GHz, 15-channel spread spectrum radio |
| Wallbox Volume | 5.75 cubic inches |
| Weight | 0.12 lb. (0.05 kg) |
| Shipping Weight | 0.22 lb. (0.10 kg) |
| Available Colors | |
| C4-KD120-xx and C4-KD277-xx | WH, LA, IV, BR, BL, SW, MB, BI, AU |
| C4-KD240-xx | WH, BL, SW, MB, BI, AU |
| Available Accessories | |
| Faceplate, 1 Gang (C4-FP1-xx) | WH, LA, IV, BR, BL, SW, MB, BI, AU, SN, SS, VB |
| Faceplate, 2 Gang (C4-FP2-xx) | WH, LA, IV, BR, BL, SW, MB, BI, AU, SN, SS, VB |
| Faceplate, 3 Gang (C4-FP3-xx) | WH, LA, IV, BR, BL, SW, MB, BI, AU, SN, SS, VB |
| Faceplate, 4 Gang (C4-FP4-xx) | WH, LA, IV, BR, BL, SW, MB, BI, AU, SN, SS, VB |
| Color Kit (C4-CKKD-xx) | WH, LA, IV, BR, BL, SW, MB, BI, AU |
| Engraved Button, Single High (C4-EBD1H-xx) | WH, LA, IV, BR, BL, SW, MB, BI, AU |
| Engraved Button, Double High (C4-EBD2H-xx) | WH, LA, IV, BR, BL, SW, MB, BI, AU |
| Engraved Button, Triple High (C4-EBD3H-xx) | WH, LA, IV, BR, BL, SW, MB, BI, AU |

Gloss Colors: WH=White, LA=Light Almond, IV=Ivory, BR=Brown, BL=Black

Satin Colors: SW=Snow White, MB=Midnight Black, BI=Biscuit, AU=Aluminum

Metal Finishes: SN=Satin Nickel, SS=Stainless Steel, VB=Venetian Bronze

